

Kodak Scan Station 100 Embedded Version 2.0 Configuration Organizer 2.0 02/15/08

Installation Instructions

Download the new Scan Station SW and place in a temp directory or you may launch the self-executable from the web.

Double click and launch the self-executable software update you have just down loaded.

| | |
|---|---|
| It contains the following files: | |
| New Configuration Application ver 2.0 | ConfigurationApp.exe |
| Supporting DLLs | ChilkatDotNet2.dll, PerlRT60.dll, pdfmelddn.dll |
| New Scan Station Conf ICON | configurationapp.ico |
| Kodak Scan Station embedded SW ver 2.0 | KSS100update.exe |
| An ADMIN FILE to enable the SW update | kss100.xml |
| This Installation Instructions | KSSv2.0_installation_Instructions.pdf |

NEW Configuration Application 2.0

- By default, the unzip utility will automatically replace the new ConfigurationApp.exe and add the new ICON file in the **default location** where the Kodak Scan Station 100 Configuration Organizer Application is currently installed on your PC. If you have installed the Configuration Organizer Application in a different location other then the default, then please manually place the ConfigurationApp.exe and all the other associated files in that new location and overwrite the old files.
- This new Configuration Organizer Application should now be used for editing current and creating new Scan Station and User profiles.

Updating the Scan Station to the NEW SW 2.0

Copy the KSS100update.exe update file ver 2.0.0.15 and the kss100.xml file to a blank flash drive.

- These files were automatically loaded into the default location for the configuration organizer
- Locate these files in this path:
C:\Program Files\Kodak\Scan Station 100\embedded 2.0.0.15 update
- Insert the USB flash drive into the Kodak Scan Station 100, and follow all update prompts.
- Reboot the Scan station.
- Check the version of software loaded on the scan station by scrolling to the "i" icon.

Once this USB pen is created with these two files, it may be used to repeat additional Scan Stations updates.

New Features for this release are:

For a more detailed description and use of these new features please review the new administrators and Users guides.

- Includes Configuration Organizer and Scan Station software V 2.0.0.15
- New Inbound and outbound FAX¹ capability
- New PDF private key encryption
- New advance selection mode for Configuration Organizer
- New activity logging
- New Task Groupings for pre-selected profiles
- Option to configure scanner profile settings to specific destinations
- Option to scan multiple pages and create single page PDFs
- Option to enable/disable scan to a flash drive
- Option to rename email subject line
- Option to enter file name prior to scanning

¹Fax Capability requires the Kodak Scan Station 100 Fax Modem Accessory and a Scan Station with a serial number higher than 45325000 - Catalog Number 128 0528 (Accessory includes: USB Cable, phone cable, and USB Modem)

Kodak Scan Station 100 with a Serial Number of 45325000 or higher is Fax Modem ready.

Kodak Scan Station 100 with a Serial Number below 45325000 was not manufactured with the device drivers required for the Fax modem accessory. Therefore the FAX feature is not available with a Scan Station with a serial number below 45325000. Updating a Kodak Scan Station 100 with a serial number below 45325000 to software version 2.0 will have all the above new features available with the exception of fax. If you are interested in fax capability on your Scan Station with a serial number below 45325000, contact Kodak Service at: US&C 1-800-822-1414.

All other regions please go to www.kodak.com/go/disupport to contact Service for upgrade options.