

Kodak Canada ULC
4225 Kincaid St
Burnaby, B.C., Canada
V5G 4P5
Tel: 1.604.451.2700
Fax: 1.604.437.9891



Technical Bulletin

Internal: 750-00340H-EN Rev O

Release date: September 1, 2021

Qualified Thermal Media Bulletin

Overview

This document lists thermal media that are qualified for use on Kodak thermal CTP systems, with specific information regarding the different plate handling options available. This document only contains currently available CTP devices. For legacy devices, and for plate throughput estimates and qualified screens, see the CTP Media Imaging Performance Database.

If a media is not listed in this document, it is not qualified on Kodak CTP systems.

This document is updated on the first day of each month. If you are using a copy more than one month old, download the latest version.

How to Use This Document

Information is divided into categories based on the following device formats:

- 4&8 page commercial CTP
- VLF Commercial CTP
- Newspaper CTP (Standard resolutions of 1200 dpi and 1270 dpi)
- Newspaper CTP (Commercial resolutions of 2400 dpi and 2540 dpi)
- Proofing CTP

Each category is further divided based on device types and automation options.

Find the requested device configuration in the appropriate table and look for the requested plate in the plate list. The intersection of the device and plate will have the qualification status. An additional column indicates whether or not the plate can be imaged at the full device specification for the available speed models. The speed models which Allow full speed imaging are listed.

Exclusion of a plate indicates that it is not qualified.

Device Configuration Definitions

- AL – Autoloader
- APL – Automatic Pallet Loader
- AU – Auto-Unload
- CL – Continuous Load
- MCU – Multi Cassette Unit
- M – Manual. Equivalent to SA
- SA – Semi-Automatic
- SCU – Single Cassette Unit
- SPL/MPL – Single Pallet Loader / Multi Pallet Loader

Details on automation options can be found in the device specifications.

Note that automation options are unique to a device type. For example, the APL option for the Magnus 800 is different from the APL option for the Magnus VLF, and each is tested and qualified separately.

Qualification Status Definitions

- **Q** – Qualified
This indicates that a plate is fully compatible with a particular device combination.
- **L** – Limited Qualification
A plate is qualified on a given device configuration but restrictions apply. Consult the CTP Media Imaging Performance Database for more details.
- **NQ** – Not Qualified
This indicates that a plate has either not been tested or has failed the qualification tests for a given device configuration.
- **P** – Pending
A temporary qualification status used for new plates that are in the process of being tested or qualified plates whose qualification is about to expire and re-qualification tests have not yet taken place. A plate with a 'Pending' status may continue to be qualified, or its qualification status may change, or it may become not qualified depending on the results of the re-qualification tests. A plate with a 'Pending' status will be supported by Kodak.
- **E** – Expired
Indicates that the qualification status has expired. This is equal to Not Qualified. Plates with expired qualification status are periodically removed from this bulletin. A plate that does not appear in this bulletin is assumed to be Not Qualified.

Debris Removal Requirements

Starting with the May 2019 version of the bulletin, debris removal requirements are now displayed. Columns labeled 'UDRC' have been added to each device category. UDRC requirements depend on plate type and device speed.

If some but not all speeds require UDRC with a particular plate, then those speeds will be listed in the UDRC column (for example, X, W). Otherwise, the following are used:

- ALL – UDRC-BP Required on all models/speeds
- NR - UDRC-BP Not Required
- EV – UDRC-BP with External Venting Required
- N/A – plate is not qualified on the device, and/or UDRC is unavailable on the device

Notes

1. Magnus VLF with MCU or APL
In addition to plate type, throughput depends on plate size(s), number of plates (single or dual loading) and loading orientation. Consult the CTP Media Imaging Performance Database for plates/hour estimates.
2. Screening qualification depends on the specific device configuration and plate type. The screening qualification for a specific device and plate combination in the CTP Media Imaging Performance Database overrides the individual plate and device specifications.
3. For Magnus® 800 APL, plates with an asterisk(*) next to the qualification status are qualified for SCU mode ONLY.
4. For Generation News® devices, plates with an asterisk(*) are NOT qualified on dual-head models (Z speed).
5. W and T speeds are new. Plates may not be qualified for all speed options on a given device. Consult the CTP Media Imaging Performance Database for more information.

Links

CTP Media Imaging Performance Database:

<https://services.knowledge.en.kodak.com>

Sales Information Library:

<https://partnerplace.kodak.com>

Contact

Please direct any questions or comments regarding the content of this document to Tony Skrjanec:

<mailto:tony.skrjanec@kodak.com>



4 and 8 Page CTP for Kodak Media

| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|--|--------------------------|----|---------|---------|------------|--|------|----|---------|------------|--|------|----|---------|------------|--|------|-----|------------|--------------------------------------|-----|
| | Handling Options | CL | SCU MCU | SPL MPL | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL |
| Electra XD | Q | Q | Q | F,X | X,Z,W,T | Q | Q | Q | ALL | W | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| ElectraMAX | Q | Q | Q | F,X | X,Z,W,T | Q | Q | Q | ALL | W | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| DITR 4401 | NQ | NQ | NQ | N/A | N/A | B | NQ | NQ | NONE | EV | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | NQ | N/A |
| Sonora XP | Q | Q | Q | F | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora X | Q | Q | Q | F,X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora UV | Q | Q | Q | F | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora XJ | Q | Q | Q | F | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora CX | Q | Q | Q | F,X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora CX2 | Q | Q | Q | F,X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sonora XTRA-2 and XTRA-3 (EAMER) | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Sonora XTRA | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| SwordMAX | Q | Q | Q | F,X | X,Z,W,T | Q | Q | Q | ALL | W | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Trillian SP | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |



| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|------------------|--------------------------|---------|---------|------------|---------|--|----|---------|------------|------|--|----|---------|------------|------|--|----|------------|------|--------------------------------------|------------|
| Handling Options | CL | SCU MCU | SPL MPL | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL | Full Speed |
| ThermalNews PT | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Capricorn XR | Q | Q | Q | ALL | X,Z,W,T | Q | Q | Q | ALL | W | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Capricorn GT | Q | Q | Q | F | R | Q | Q | Q | ALL | ALL | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| Sword XD / XDW | Q | Q | NQ | ALL | R | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| TP-U | Q | NQ | NQ | F | R | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| TP-W | Q | Q | NQ | ALL | R | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| TN-R | Q | NQ | NQ | ALL | R | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |



4 and 8 Page CTP for Non-Kodak Media

| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|------------------|--------------------------|-------------------|------------|---------------|---------|--|----|------------|---------------|------|--|----|------------|---------------|------|--|----|---------------|------|--------------------------------------|---------------|
| | CL | SCU DCU MCU | SPL MPL | Full Speed | UDRC | SA | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL | Full Speed |
| Agfa | | | | | | | | | | | | | | | | | | | | | |
| Adamas | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Avatar T ZP | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| Azura TE | Q | Q | NQ | F | R | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| Azura TU | Q | Q | NQ | F | R | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| Eclipse | Q | Q | NQ | F | NR | Q | Q | Q | ALL | NR | Q | Q | Q | NONE | N/A | Q | Q | NONE | N/A | Q | YES |
| Energy Elite Pro | Q | Q | NQ | F,X | ALL | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | Q | ALL | N/A | Q | YES |
| Energy Elite Eco | Q | Q | NQ | X,W | X,Z,W,T | Q | Q | Q | ALL | W | NQ | NQ | NQ | N/A | N/A | NQ | Q | ALL | N/A | Q | YES |
| Energy Verve | Q | Q | NQ | F,X | NR | Q | Q | Q | ALL | NR | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| P970 | Q | Q | NQ | F, X | ALL | Q | Q | NQ | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| Fujifilm | | | | | | | | | | | | | | | | | | | | | |
| SUPERIA LH-PJ | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |



| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|------------------|--------------------------|-------------|---------|------------|------|--|----|---------|------------|------|--|----|---------|------------|------|--|----|------------|------|--------------------------------------|------------|
| Handling Options | CL | SCU DCU MCU | SPL MPL | Full Speed | UDRC | SA | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL | Full Speed |
| SUPERIA LH-PJ2 | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/Q | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PJE | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA XP-F | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PA | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PK | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PL | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PLE | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA XP-L | Q | Q | Q | ALL | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA LH-PXE | Q | Q | P | F, X | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA XL-T | Q | Q | P | F, X | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | NQ | N/A | NQ | NQ | N/A | N/A | Q | YES |
| SUPERIA ZP | Q | Q | Q | F, X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |



| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|-------------------|--------------------------|-------------|---------|------------|------------|--|----|---------|------------|------|--|----|---------|------------|------|--|----|------------|------|--------------------------------------|------------|
| Handling Options | CL | SCU DCU MCU | SPL MPL | Full Speed | UDRC | SA | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL | Full Speed |
| SUPERIA Ecomaxx-T | Q | Q | Q | F, X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| SUPERIA ZD | Q | Q | P | F, X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | S | N/A | Q | Q | S | N/A | Q | YES |
| SUPERIA ZD-II | Q | Q | NQ | F, X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| SUPERIA ZD-III | Q | Q | P | F, X | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Huaguang | | | | | | | | | | | | | | | | | | | | | |
| TP-A | Q | Q | NQ | F, X | W, T | Q | Q | Q | ALL | W | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| TP-U | Q | Q | NQ | F, X | ALL | Q | Q | Q | ALL | ALL | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | Q | YES |
| Ipagsa | | | | | | | | | | | | | | | | | | | | | |
| Universe O2 | Q | Q | NQ | F, X, Z | X, Z, W, T | Q | Q | Q | All | W | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| Toray | | | | | | | | | | | | | | | | | | | | | |
| GU8 | Q | Q | NQ | ALL | NR | NQ | NQ | NQ | N/A | NR | NQ | NQ | NQ | N/A | N/A | NQ | NQ | N/A | N/A | NQ | N/A |
| TAC-CD5 | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | Q | ALL | Q | YES |
| VG5 | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | Q | ALL | Q | YES |



| Device | Magnus Q800 F, X, W*, T* | | | | | Trendsetter Q400 F, X, W* Trendsetter Q800 F, X, W* | | | | | Achieve T400 S, F Achieve T800 S, F | | | | | Veriset T400 S, F Veriset T800 S, F | | | | Veriset Plus F Speed AL + UDRC | |
|--------------------------------|--------------------------|-------------------|------------|---------------|------|--|----|------------|---------------|------|--|----|------------|---------------|------|--|----|---------------|------|--------------------------------------|---------------|
| Handling Options | CL | SCU DCU MCU | SPL MPL | Full Speed | UDRC | SA | AL | SCU MCU | Full Speed | UDRC | M AU | AL | SCU MCU | Full Speed | UDRC | M AU | AL | Full Speed | UDRC | AL | Full Speed |
| VG7 | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | Q | ALL | Q | YES |
| VH5 | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | Q | ALL | Q | YES |
| GC / SC / MC | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| CA / GA / LA / MA / WA | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |
| CB / GB / LB / MB / SB / WB | Q | Q | NQ | ALL | NR | Q | Q | Q | ALL | NR | Q | Q | Q | ALL | N/A | Q | Q | ALL | N/A | Q | YES |



VLF Commercial CTP for Kodak Media

| Device | Magnus VLF Q2400/Q3600 F, X, Z, W* | | | | | Trendsetter Q1600 F,X,W | | | Trendsetter Q2400 F,X,W Trendsetter Q3600 F,X,W | | |
|--------------------------------------|------------------------------------|-----|-----|---------------|------|-------------------------|---------------|-------|--|---------------|-------|
| | SA CL | MCU | APL | Full Speed | UDRC | SA | Full Speed | UDRC | SA | Full Speed | UDRC |
| Electra XD | Q | Q | Q | F, X | Z, W | Q | ALL | W | Q | F,X | W |
| ElectraMAX | Q | Q | Q | F, X | Z, W | Q | ALL | W | Q | F,X | W |
| DITR 4401 | NQ | NQ | NQ | N/A | EV | Q | NONE | EV | Q | NONE | EV |
| Sonora XP | Q | Q | Q | NONE | NR | Q | F,X | NR | Q | NONE | NR |
| Sonora X | Q | Q | Q | F | NR | Q | ALL | NR | Q | F,X | NR |
| Sonora UV | Q | Q | Q | NONE | NR | Q | F,X | NR | Q | NONE | NR |
| Sonora XJ | Q | Q | Q | NONE | NR | Q | ALL | NR | Q | NONE | NR |
| Sonora CX | Q | Q | Q | F | NR | Q | ALL | NR | Q | F,X | NR |
| Sonora CX2 | Q | Q | Q | F | NR | Q | ALL | NR | Q | F,X | NR |
| Sonora XTRA-2 and EXTRA-3 (EAMER) | Q | Q | Q | ALL | NR | Q | ALL | NR | Q | ALL | NR |
| Sonora XTRA | Q | Q | Q | ALL | NR | Q | ALL | NR | Q | ALL | NR |
| SwordMAX | Q | Q | Q | F, X | Z, W | Q | ALL | W | Q | F,X | W |
| Trillian SP | Q | Q | Q | ALL | NR | Q | ALL | NR | Q | ALL | NR |
| ThermalNews PT | Q | Q | Q | ALL | NR | Q | ALL | NR | Q | ALL | NR |
| Capricorn GT | Q | Q | Q | NONE | ALL | Q | ALL | ALL | Q | F | ALL |
| Capricorn XR | Q | Q | NQ | F, X | Z, W | Q | ALL | R*- W | Q | F,X | R*- W |
| Sword J | Q | NQ | NQ | F | ALL | Q | F,X | ALL | Q | F | ALL |
| Sword XD | Q | NQ | NQ | F, X | R | Q | F,X | ALL | Q | F | ALL |
| TP-U | Q | L | NQ | NONE | R | Q | F,X | ALL | Q | NONE | ALL |
| TP-W | Q | L | NQ | F, X | R | Q | ALL | ALL | Q | F,X | ALL |



| Device | Magnus VLF Q2400/Q3600 F, X, Z, W* | | | | | Trendsetter Q1600 F,X,W | | | Trendsetter Q2400 F,X,W Trendsetter Q3600 F,X,W | | |
|--------|------------------------------------|-----|-----|---------------|------|-------------------------|---------------|------|--|---------------|------|
| | SA CL | MCU | APL | Full Speed | UDRC | SA | Full Speed | UDRC | SA | Full Speed | UDRC |
| TN-R | Q | NQ | NQ | ALL | R | Q | ALL | ALL | Q | ALL | ALL |

VLF Commercial CTP for Non-Kodak Media

| Device | Magnus VLF Q2400/Q3600 F, X, Z, W* | | | | | Trendsetter Q1600 F,X,W | | | Trendsetter Q2400 F,X,W Trendsetter Q3600 F,X,W | | |
|------------------|------------------------------------|-----|-----|---------------|------|-------------------------|---------------|------|--|---------------|------|
| | SA CL | MCU | APL | Full Speed | UDRC | SA | Full Speed | UDRC | SA | Full Speed | UDRC |
| Agfa | | | | | | | | | | | |
| Adamas | Q | Q | Q | F, X | NR | Q | ALL | NR | Q | F | NR |
| Azura TE | Q | Q | NQ | NONE | ALL | Q | NONE | ALL | Q | NONE | ALL |
| Azura TU | Q | Q | Q | NONE | ALL | Q | NONE | ALL | Q | NONE | ALL |
| Eclipse | Q | Q | Q | F | NR | Q | ALL | NR | Q | F | NR |
| Energy Elite Pro | Q | Q | Q | F | ALL | Q | ALL | ALL | Q | F,X | ALL |
| Energy Elite Eco | Q | NQ | NQ | ALL | Z, W | Q | ALL | W | Q | F,X | W |
| Energy Verve | Q | Q | Q | ALL | NR | Q | ALL | NR | Q | ALL | NR |
| P970 | Q | Q | Q | F | ALL | Q | ALL | ALL | Q | F,X | ALL |
| Fujifilm | | | | | | | | | | | |
| SUPERIA LH-PJ | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F, X | ALL |
| SUPERIA LH-PJ2 | Q | Q | Q | F,X | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA LH-PJE | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F, X | ALL |
| SUPERIA XP-F | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA LH-PA | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F,X | ALL |



| Device | Magnus VLF Q2400/Q3600 F, X, Z, W* | | | | | Trendsetter Q1600 F,X,W | | | Trendsetter Q2400 F,X,W Trendsetter Q3600 F,X,W | | |
|-------------------|------------------------------------|-----|-----|---------------|------|-------------------------|---------------|------|--|---------------|------|
| | SA CL | MCU | APL | Full Speed | UDRC | SA | Full Speed | UDRC | SA | Full Speed | UDRC |
| SUPERIA LH-PK | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA LH-PL | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F, X | ALL |
| SUPERIA LH-PLE | Q | Q | Q | F, X | ALL | Q | ALL | ALL | Q | F, X | ALL |
| SUPERIA XP-L | Q | NQ | Q | F, X | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA LH-PXE | Q | Q | P | F | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA XL-T | Q | Q | Q | F | ALL | Q | ALL | ALL | Q | F,X | ALL |
| SUPERIA ZP | Q | Q | Q | None | NR | Q | ALL | NR | Q | None | NR |
| SUPERIA Ecomaxx-T | Q | Q | Q | None | NR | Q | ALL | NR | Q | None | NR |
| SUPERIA ZD | Q | Q | Q | None | NR | Q | ALL | NR | Q | None | NR |
| SUPERIA ZD-II | Q | Q | Q | F,X | NR | Q | ALL | NR | Q | F,X | NR |
| SUPERIA ZD-III | Q | Q | Q | F,X | NR | Q | ALL | NR | Q | F,X | NR |
| Huaguang | | | | | | | | | | | |
| TP-A | Q | Q | Q | F,X | W | Q | ALL | W | Q | F,X | W |
| TP-U | Q | Q | Q | F,X | ALL | Q | ALL | ALL | Q | F,X | ALL |
| Ipagsa | | | | | | | | | | | |
| Universe O2 | Q | Q | Q | F, X | Z, W | Q | ALL | W | Q | F,X | W |
| Toray | | | | | | | | | | | |
| TAC-CD5 | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |
| VG5 | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |
| VG7 | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |
| VH5 | NQ | NQ | NQ | N/A | NR | NQ | N/A | NR | NQ | N/A | NR |



| Device | Magnus VLF Q2400/Q3600 F, X, Z, W* | | | | | Trendsetter Q1600 F,X,W | | | Trendsetter Q2400 F,X,W Trendsetter Q3600 F,X,W | | |
|--------------------------------|------------------------------------|-----|-----|---------------|------|-------------------------|---------------|------|--|---------------|------|
| Handling Options | SA CL | MCU | APL | Full Speed | UDRC | SA | Full Speed | UDRC | SA | Full Speed | UDRC |
| GC / SC / MC | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |
| CA / GA / LA / MA / WA | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |
| CB / GB / LB / MB / SB / WB | Q | NQ | NQ | ALL | NR | Q | ALL | NR | Q | F,X | NR |



Newspaper CTP: Standard Resolutions of 1200 dpi and 1270 dpi for Kodak Media

| Device | TS NEWS S, F, V | | | | Generation NEWS V, Z | | | Achieve NEWS F (1200 dpi only) | | | |
|-------------------------------------|-----------------|------------|---------------|------|----------------------|---------------|------|--------------------------------|------------|---------------|------|
| | AL | SCU MCU | Full Speed | UDRC | AL | Full Speed | UDRC | AL | SCU MCU | Full Speed | UDRC |
| Electra XD | Q | Q | S | NR | Q | NONE | NR | Q | Q | ALL | N/A |
| Electra MAX | NQ | NQ | N/A | NR | NQ | N/A | NR | Q | Q | ALL | N/A |
| Sonora XP | Q | Q | S | NR | Q | NONE | NR | Q | Q | NONE | N/A |
| Sonora X-N | Q | Q | S | NR | Q | NONE | NR | Q | Q | NONE | N/A |
| Sonora News | Q | Q | S | NR | Q | NONE | NR | Q | Q | NONE | N/A |
| Sonora XTRA-N | Q | Q | ALL | NR | Q | NONE | NR | Q | Q | ALL | N/A |
| Sonora XTRA-2 and XTRA-3 (EAMER) | Q | Q | ALL | NR | Q | ALL | NR | Q | Q | F | N/A |
| Sonora XTRA | Q | Q | ALL | NR | Q | ALL | NR | Q | Q | F | N/A |
| ThermalNEWS Gold | Q | NQ | ALL | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |
| ThermalNEWS PT | Q | Q | ALL | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |
| ThermalNEWS SP | Q | Q | S | NR | Q | NONE | NR | Q | Q | ALL | N/A |
| TN-NEWS II | Q | NQ | ALL | NR | NQ | N/A | NR | NQ | NQ | N/A | N/A |
| TN-R | Q | NQ | S | ALL | NQ | N/A | ALL | NQ | NQ | N/A | N/A |
| Trillian SP | Q | Q | ALL | NR | Q | V | NR | Q | Q | ALL | N/A |



Newspaper CTP: Standard Resolutions of 1200 dpi and 1270 dpi for Non-Kodak Media

| Device | TS NEWS S, F, V | | | | Generation NEWS V, Z | | | Achieve News F (1200 dpi only) | | | |
|-----------------------------|-----------------|---------|------------|------|----------------------|------------|------|--------------------------------|---------|------------|------|
| Handling Options | AL | SCU MCU | Full Speed | UDRC | AL | Full Speed | UDRC | AL | SCU MCU | Full Speed | UDRC |
| Agfa | | | | | | | | | | | |
| Avatar T CF | Q | Q | S | NR | Q | NONE | N/A | Q | Q | F | NR |
| Avatar T ZP | Q | Q | ALL | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |
| Azura TU | Q | Q | S | ALL | NQ | N/A | ALL | NQ | NQ | N/A | N/A |
| Azura TE | Q | Q | S | ALL | NQ | N/A | ALL | NQ | NQ | N/A | N/A |
| Energy Elite Pro | Q | Q | S, F | ALL | NQ | N/A | ALL | NQ | NQ | N/A | N/A |
| Energy Elite Eco | Q | Q | ALL | NR | NQ | N/A | NR | NQ | NQ | N/A | N/A |
| Energy Verve | Q | Q | ALL | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |
| Thermostar P970 | Q | Q | S | ALL | NQ | N/A | ALL | NQ | NQ | N/A | N/A |
| Fujifilm | | | | | | | | | | | |
| SUPERIA ZD | Q | Q | S | NR | Q | None | NR | Q | Q | None | NR |
| SUPERIA ZD-N | Q | Q | S | NR | Q | None | NR | Q | Q | None | NR |
| Verico Technology | | | | | | | | | | | |
| Zahara Newz | Q | Q | S | NR | Q | NONE | NR | Q | Q | NONE | NR |
| Toray | | | | | | | | | | | |
| CA / GA / LA / MA / WA | NQ | NQ | N/A | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |
| CB / GB / LB / MB / SB / WB | NQ | NQ | N/A | NR | Q | ALL | NR | NQ | NQ | N/A | N/A |



Newspaper CTP: Commercial Resolutions of 2400 dpi and 2540 dpi for Kodak Media

| Device | Trendsetter NEWS S, F | | | | Generation NEWS V | | |
|--------------------------|-----------------------|----|-----------|------------|-------------------|------|------------|
| | Handling Options | AL | SCU / MCU | Full Speed | UDRC | AL | Full Speed |
| Electra XD | Q | Q | ALL | NR | NQ | ALL | NR |
| ElectraMAX | Q | Q | ALL | NR | NQ | N/A | NR |
| Sonora XP | Q | Q | ALL | NR | Q | NONE | NR |
| Sonora News | Q | Q | ALL | NR | Q | NONE | NR |
| Sonora XTRA-N | Q | Q | ALL | NR | Q | ALL | NR |
| Sonora XTRA-2 and XTRA-3 | Q | Q | ALL | NR | Q | V | NR |
| Sonora XTRA | Q | Q | ALL | NR | Q | V | NR |
| SwordMAX | Q | Q | ALL | NR | Q | ALL | NR |
| Trillian SP | Q | Q | ALL | NR | NQ | N/A | NR |
| Capricorn GT | Q | Q | ALL | ALL | NQ | N/A | N/A |
| Capricorn XR | Q | Q | ALL | NR | NQ | N/A | NR |
| Sword J | Q | NQ | ALL | ALL | NQ | N/A | ALL |
| Sword XD | Q | NQ | ALL | ALL | NQ | N/A | ALL |
| ThermalNEWS Gold | Q | NQ | ALL | NR | Q | ALL | NR |
| ThermalNEWS PT | Q | Q | ALL | NR | Q | ALL | NR |
| ThermalNews SP | Q | Q | ALL | NR | Q | ALL | NR |
| TN-NEWS II | Q | NQ | ALL | NR | NQ | N/A | NR |
| Kodak TN-R | Q | NQ | ALL | ALL | NQ | N/A | ALL |
| TP-U | Q | NQ | ALL | ALL | NQ | N/A | ALL |



Newspaper CTP: Commercial Resolutions of 2400 dpi and 2540 dpi for Non-Kodak Media

| Device | Trendsetter NEWS S, F | | | | Generation NEWS V | | |
|------------------|-----------------------|-----------|------------|------|-------------------|------------|------|
| Handling Options | AL | SCU / MCU | Full Speed | UDRC | AL | Full Speed | UDRC |
| Agfa | | | | | | | |
| Avatar T CF | Q | Q | S, F | NR | Q | V | NR |
| Avatar T ZP | Q | Q | ALL | NR | Q | ALL | NR |
| Azura TU | Q | Q | S | ALL | NQ | N/A | ALL |
| Azura TE | Q | Q | S | ALL | NQ | N/A | ALL |
| Energy Elite Pro | Q | Q | ALL | ALL | NQ | N/A | ALL |
| Energy Elite Eco | Q | Q | ALL | NR | NQ | N/A | NR |
| Energy Verve | Q | Q | ALL | NR | Q | ALL | NR |
| Thermostar P970 | Q | Q | ALL | ALL | NQ | N/A | ALL |
| Fujifilm | | | | | | | |
| SUPERIA LH-PJ | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PJ2 | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PJE | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA XP-F | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PA | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PK | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PL | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PLE | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA XP-L | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA LH-PXE | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA XL-T | Q | Q | NONE | ALL | NQ | N/A | N/A |



| Device | Trendsetter NEWS S, F | | | | Generation NEWS V | | |
|-----------------------------|-----------------------|-----------|------------|------|-------------------|------------|------|
| | AL | SCU / MCU | Full Speed | UDRC | AL | Full Speed | UDRC |
| SUPERIA ZP | Q | Q | ALL | ALL | NQ | N/A | N/A |
| SUPERIA Ecomaxx-T | Q | Q | ALL | NR | NQ | N/A | N/A |
| SUPERIA ZD | Q | Q | ALL | NR | Q | None | NR |
| SUPERIA ZD-N | Q | Q | ALL | NR | Q | None | NR |
| Huaguang | | | | | | | |
| TP-A | Q | Q | ALL | NR | NQ | N/A | N/A |
| TP-U | | Q | ALL | ALL | NQ | N/A | N/A |
| Verico Technology | | | | | | | |
| Zahara Newz | Q | Q | ALL | NR | Q | ALL | NR |
| Toray | | | | | | | |
| CA / GA / LA / MA / WA | NQ | NQ | N/A | NR | Q | ALL | NR |
| CB / GB / LB / MB / SB / WB | NQ | NQ | N/A | NR | Q | ALL | NR |

Updates to this version

No changes.

About Kodak

The leading provider of graphic communications solutions worldwide, Kodak offers image capture systems; professional color, copydot, and high-speed document scanning systems; inkjet printing and proofing systems; workflow and color management software; thermal imaging devices for film, plates, and proofs; high-quality proofing media, printing plates, and recording film; on-demand color and black-and-white printing systems; data storage products; and professional services. With corporate headquarters located in Rochester, N.Y., Kodak (NYSE: EK) has the largest global sales force and is committed to a digitally oriented growth strategy.

© Kodak, 2020. All rights reserved. Kodak, Creo, Lotem, Magnus, ThermoFlex, Trendsetter, Proofsetter Spectrum, Trendsetter Spectrum, Capricorn, ExThermo, Flexcel, Matchprint, Sword, Sword Excel, Sword Ultra, Thermal Direct, and Thermal Gold are trademarks of Kodak. Acrobat, Adobe, Distiller, Illustrator, Photoshop, and PostScript are trademarks of Adobe Systems Incorporated. Apple, AppleShare, AppleTalk, iMac, ImageWriter, LaserWriter, Mac OS, Power Macintosh, and TrueType are registered trademarks of Apple Computer, Inc. Macintosh is a trademark of Apple Computer, Inc., registered in the U.S.A. and other countries. Hexachrome, PANTONE, PANTONE Goe, PANTONE Hexachrome, and PANTONE MATCHING SYSTEM are the property of Pantone, Inc. XEROX is a trademark of XEROX CORPORATION.

Technical data subject to change without notice.